

ISSN 2310-6697

otoiser—open transactions on independent scientific-engineering research

FUNKTECHNIKPLUS # JOURNAL

Théorie—Expérimentation—Métrologie—Logiciel—Applications

ISSUE 3 – FRIDAY 31 JANUARY 2014 – YEAR 1

REPRINT

Near-field Method in Solving Inverse Scattering Problem of Spherical Electromagnetic Waves in Chiral Media

Nikolaos M. Berketis



*This small European Journal is
In the Defense of Honesty in Science and Ethics in Engineering*

Publisher – otoiser—open transactions on independent scientific engineering research, www.otoiser.org—info@otoiser.org, Hauptstraße 52, 2831 Scheiblingkirchen, Austria

Language – We declare the origins of the Journal by using in the cover page English, German and French, as well as, a Hellenic vignette. However, since we recognize the dominance of US English in the technical literature, we adopted it as the Journal's language, although it is not our native language.

Focus – We consider Radio–FUNK, which still creates a vivid impression of the untouchable, and its Technology–TECHNIK, from an Advanced–PLUS point of view, Plus–PLUS Telecommunications Engineering, Electrical Engineering and Computer Science, that is, we dynamically focus at any related scientific-engineering research regarding Théorie, Expérimentation, Métrologie, Logiciel, ou Applications.

Scope – We emphasize this scope broadness by extending the title of the Journal with a Doppelkreuz-Zeichen # which we use as a placeholder for substitution of our Editorial Team disciplines: # Telecommunications etc. as above, or # High Voltage, # Software Engineering, # Simulation etc. as below.

Frequency – We publish 3 issues per year: on 31st of January, on 31st of May, and on 30th of September, as well as, an extra issue every 3 papers and a volume every 2 years.

Editions – We increase the edition number of an issue only when is needed to reform one or more of its papers—thus to increase their version numbers—but we keep unchanged its 1st edition date shown on its front page and we number its pages sequentially from 1. We count the editions of *About* separately.

Format – We use a fixed-space font, hyphenation, justification, unfixed word spacing, and the uncommon for Journals A5 (half A4) page size to achieve WYSIWYG printing and clear reading of 2 to 4 side-by-side pages on wide-screen displays

Printing-on-Demand – We can email gratis PDFs at 300-4000 dpi in booklet page scaling of either brochure or book type.

Copyright – We publish under a Creative Commons Attribution, CC-BY 3.0 Unported or CC-BY 4.0 International, License only.

Please download the latest *About* edition from
about.ftpj.otoiser.org

Editorial Team**# Electrical Engineering**

High Voltage Engineering # Insulating Materials

Professor Michael Danikas, mdanikas@ee.duth.gr
EECE, Democritus University of Thrace, Greece

Electrical Machines # Renewable Energies # Electric Vehicles

Assistant Professor Athanasios Karlis, akarlis@ee.duth.gr
EECE, Democritus University of Thrace, Greece

Computer Science

Computer Engineering # Software Engineering # Cyber Security

Professor Vasilis Katos, vkatos@bournemouth.ac.uk
Head of Computer and Informatics Dept, Bournemouth Univ, UK

Internet Engineering # Learning Management Systems

Lecturer Sotirios Kontogiannis, skontog@gmail.com
Business Administration Dept, TEI, Western Macedonia, Greece

Hypercomputation # Fuzzy Computation # Digital Typography

Dr. Apostolos Syropoulos, asyropoulos@yahoo.com
BSc-Physics, MSc-Computer Science, PhD-Computer Science
Independent Researcher, Xanthi, Greece

Telecommunications Engineering

Applied EM Electromagnetics # Applied Mathematics

Dr. Nikolaos Berketis, nberketis@gmail.com
BSc-Mathematics, MSc-Applied Maths, PhD-Applied Mathematics
Independent Researcher, Athens, Greece

Antennas # Metrology # EM Software # Simulation # Virtual Labs

Applied EM # Education # FLOSS # Amateur Radio # Electronics

Dr. Nikolitsa Yannopoulou, yin@arg.op4.eu *

Diploma Eng-EE, MEng-Telecom-EECE, PhD-Eng-Antennas-EECE
Independent Researcher, Scheiblingkirchen, Austria
Dr. Petros Zimourtopoulos, pez@arg.op4.eu *

BSc-Physics, MSc-Radio-Electronics, PhD-Antennas-EE
Independent Researcher, Scheiblingkirchen, Austria

* Copy & Layout Editing - Proof Reading - Issue & Web Management

Technical Support

Konstantinos Kondylis, kkondylis@gmail.com

Diploma Eng-EECE, MEng-EECE, Doha, Qatar

Christos Koutsos, ckoutsos@gmail.com

Diploma Eng-EECE, MEng-EECE, Bratislava, Slovakia

Information for Authors

This is a small, but independent, low profile Journal, in which we are all—Authors, Reviewers, Readers, and Editors—free at last to be Peers in Knowledge, without suffering from Journal roles or positions, Professional–Amateur–Academic statuses, or established "impact factorizations", under the following guiding principles:

Authors – We know what Work means, we respect the Work of the Independent Researcher in Science and Engineering and we want to exhibit his Work. Thus, we decided to found this Free and Open Access Journal in which to publish this Work. Furthermore, as we care indeed for the Work of the technical author—especially a young or a beginner one—we strongly support the publication of his Work, as follows:

0 We do not demand from the author to transfer his own copyright to us. Instead, we only consider papers resulting from original research work only, and only if the author can assure us that he owns the copyright of his own paper as well as that he submits to the Journal either an original copy or a revised version of his own paper, for possible publication after review—or even for immediate republication, if this paper has already been published after review—but, in any case under a Creative Commons Attribution, CC-BY 3 Unported or CC-BY 4 International, License, only.

1 We encourage the author to submit his own paper written just in Basic English plus Technical Terminology.

2 We encourage the author even to select a pen name, which may drop it at any time to reveal his identity.

3 We encourage the author to submit an accepted for publication paper, which he was forced to decline that publication because it would be based on a review with unacceptable evaluation or derogatory comments.

4 We encourage the author to submit any paper that was rejected after a poor, impotent, inadequate, unreasonable, irresponsible, incompetent, or "just ticking" review.

5 We encourage the author to submit an unreviewed paper of his own that he uploaded on some Open Access repository.

6 We encourage the author to upload his published papers in our Journal to a truly Free Open repository like viXra.org.

7 We provide the author with a decent, express, peer review process, of up to just 4 weeks, by at least 2, either anonymous or onymous, reviewers.

8 We provide the author with the option to choose from 2 review processes: the traditional, anonymous, close one, as well as, a contemporary, onymous, open review in our private mailing list for Peer Discussion.

9 Under the Clause 0 : We immediately accept for publication a research paper directly resulting from a Project Report, or a Diploma-, Master-, or PhD-thesis, which already the author has successfully defended before a committee of experts, as long as he can mention 2 members of this committee who approved his Work.

10 Under the Clause 0 : We immediately accept for publication any paper which is not Openly Accessible on the Internet.

11 We immediately publish online a paper, as soon as it is accepted for publication in the Journal.

12 We quickly publish an extra issue—that is in excess of the 3 issues we publish a year—as soon as the review process of 3 papers is completed.

Reviewers – Every peer may voluntarily become a reviewer of the Journal in his skillfulness for as long as he wishes. In addition, each author of the Journal must review one paper in his expertness for each one of his published papers.

Readers – Every reader is a potential post-reviewer: we welcome comments and post-reviews in our private mailing list for Peer Discussion.

Editors – Every editor owns a PhD degree—to objectively prove that he really has the working experience of passing through the dominant publishing system. An editor pre-reviews a paper in order to check its compliance to our guiding principles and to select the appropriate reviewers of it. We can accept for consideration papers only in the expertise areas currently shown in the Editorial Team page, above. However, since we are very willing to amplify and extend the Scope of the Journal, we welcome the volunteer expert, in any related subject, who wants to join the Editorial Team as long as he unreservedly accepts our guiding principles.

Electronic Publishing

We regularly use the Free Libre Open Source Software Libre Office with the Free Liberation Mono font and the Freewares PDFCreator and PDF-Xchange Viewer. We also use, with some basic html code of ours: the Free Open Source Software Open Journal System OJS by the Public Knowledge Project PKP installed in our website, and the Free Open Digital Library of

Internet Archive website, where we upload Issues, Paper reprints, *About* documents, and Volumes, in both portrait and landscape orientations, for exceptionally clear online reading with the Free Open Source BookReader.

Submissions

We can consider only papers submitted in a format which is fully compatible with LibreOffice—preferably in odt format.

Legal Notice – It is taken for granted that the submitter—correspondent author accepts, without any reservation, the totality of our publication conditions as they are analytically detailed here, in this *About*, as well as, that he also carries, in the case of a paper by multiple authors, the independent will of each one of his coauthors to unreservedly accept all the aforementioned conditions for their paper.

Internet Addresses

Internet Publishing Website : ftpj.otoiser.org

Internet Archive Digital Library : archive.org/details/@ftpj

Printing-on-Demand : pod@ftpj.otoiser.org

Principal Contact : principal-contact@ftpj.otoiser.org

Technical Support : technical-support@ftpj.otoiser.org

Editorial Team-Technical Support List : etts.ftpj.otoiser.org

Peer Discussion List : peers.ftpj.otoiser.org

Submissions : sub@ftpj.otoiser.org

Sample Paper Template : template.ftpj.otoiser.org

ARG NfP AoI

Antennas Research Group

Not-for-Profit Association of Individuals *

arg.op4.eu – arg@op4.eu

Hauptstraße 52, 2831 Scheiblingkirchen, Austria

* The Constitution of Greece, Article: 12(3) 2008:

www.hellenicparliament.gr/en/Vouli-ton-Ellinon/To-Politevma

* The Hellenic Supreme Court of Civil and Penal Law:

www.areiospagos.gr/en/ – Court Rulings:Civil|A1|511|2008

This document is licensed under a Creative Commons Attribution 4.0 International License – <https://creativecommons.org/licenses/by/4.0/>

Near-field Method in Solving Inverse Scattering Problem of Spherical Electromagnetic Waves in Chiral media

Nikolaos M. Berketis *

Independent Researcher, Athens, Greece

Abstract

We have developed two methods to study an inverse scattering problem of electromagnetic waves in chiral media, for a spherical scatterer perfect conductor. The first called Far-field inverse problem was described analytical in our previous work. The second called Near-field method is given in detail in the present paper. It is a geometrical method based on the scattered fields. Using Near-field experiments, in which the scattered field is measured at the source, we solve the corresponding inverse scattering problem that is to determine the coordinates of the center and the radius of the spherical scatterer.

Introduction

We study an inverse scattering problem of electromagnetic waves with time harmonic dependence applying the method of Near-field [1]-[3]. Spherical electromagnetic waves generated by a point source incident on a spherical scatterer perfect conductor in a chiral media.

Knowing the incident and scattered wave fields in the inverse problem we are looking for the coordinates of the sphere center and its radius.

The corresponding problem is solved by geometrical methods using either energy scattering cross-section, or

the scattered fields. In the first case we refer to the inverse Far-field problem [4] and in the second case to a Near-field inverse problem.

The chiral materials exhibit the phenomenon of optical activity i.e., the phenomenon that in which the plane of polarizations of linearly polarized light is rotated as the light passes through an optically active medium.

The chirality is a property which is often found in nature and reflects the asymmetry in the spatial inversion. An electromagnetic wave into a chiral media is analyzed in a counter-clockwise

(LCP) and a clockwise (RCP) Beltrami field. Using vector spherical harmonic functions and appropriate expansions of the Beltrami fields and by extension the development of spherical electromagnetic waves in spherical wave functions, we calculate the exact solution of the scattering problem for a spherical perfect conductor in chiral media, and the corresponding back scattering [3]-[4].

In the inverse problem we calculate the scattered Near-field, when the source is in position $\mathbf{r} = \mathbf{r}_0$. A similar problem for achiral materials has been studied in the works [1], [2].

Statement of the problem

Consider a point source at the position \mathbf{r}_0 that produces spherical electromagnetic waves in a chiral media near a scatterer Ω^- , perfect conductor, i.e. the surface of the boundary condition is satisfied

$$\hat{\mathbf{n}} \times (\mathbf{E}^{inc}(\mathbf{r}) + \mathbf{E}^{sc}(\mathbf{r})) = \mathbf{0} \quad (1)$$

$$r = a$$

We consider that the exterior $\Omega^+ = \mathbb{R}^3 / \Omega^-$ of the scatterer is homogeneous chiral media with fixed chirality β , dielectric constant ϵ and magnetic permeability μ .

A spherical incident electromagnetic wave $(\mathbf{E}_{\mathbf{r}_0}^{inc}(\mathbf{r}), \mathbf{H}_{\mathbf{r}_0}^{inc}(\mathbf{r}))$ with time harmonic dependence in accordance with the Bohren transformation, analyzed in spherical Beltrami fields $\mathbf{Q}_{L,\mathbf{r}_0}^{inc}(\mathbf{r})$ and $\mathbf{Q}_{R,\mathbf{r}_0}^{inc}(\mathbf{r})$ as follows:

$$\begin{cases} \mathbf{E}_{\mathbf{r}_0}^{inc}(\mathbf{r}) = \mathbf{Q}_{L,\mathbf{r}_0}^{inc}(\mathbf{r}) + \mathbf{Q}_{R,\mathbf{r}_0}^{inc}(\mathbf{r}) \\ \mathbf{H}_{\mathbf{r}_0}^{inc}(\mathbf{r}) = \frac{1}{i\eta} (\mathbf{Q}_{L,\mathbf{r}_0}^{inc}(\mathbf{r}) - \mathbf{Q}_{R,\mathbf{r}_0}^{inc}(\mathbf{r})) \end{cases} \quad (2)$$

where $\eta = (\mu/\epsilon)^{1/2}$ is the intrinsic impedance of the chiral medium. The Beltrami fields satisfy the equations, [5], [6],

$$\begin{cases} \nabla \times \mathbf{Q}_{L,\mathbf{r}_0}(\mathbf{r}) = \gamma_L \mathbf{Q}_{L,\mathbf{r}_0}(\mathbf{r}) \\ \nabla \times \mathbf{Q}_{R,\mathbf{r}_0}(\mathbf{r}) = -\gamma_R \mathbf{Q}_{R,\mathbf{r}_0}(\mathbf{r}) \end{cases} \quad (3)$$

where γ_L, γ_R are wave numbers for Beltrami fields and are given by,

$$\gamma_L = \frac{k}{1 - k\beta}, \gamma_R = \frac{k}{1 + k\beta} \quad (4)$$

With $k = \omega(\epsilon\mu)^{1/2}$, ω being the angular frequency. The indices L and R denote the LCP and RCP fields respectively. The spherical incident Beltrami fields with suitable normalization have the form, as defined in the following works: [4] (issue 2, p. 9, relations (4), (5)), and [3].

If $\mathbf{Q}_{L,r_0}^{inc}(\mathbf{r})$ and $\mathbf{Q}_{R,r_0}^{inc}(\mathbf{r})$ are Beltrami fields corresponding via transformation to Bohren in $\mathbf{E}_{r_0}^{inc}$ and $\mathbf{H}_{r_0}^{inc}$, then the scattering problem for the perfect conductor can be formulated in the following way: be found $\mathbf{Q}_{L,r_0}^{tot}(\mathbf{r})$, $\mathbf{Q}_{R,r_0}^{tot}(\mathbf{r})$, which belong to the space $C^1(\Omega^+) \cap C(\overline{\Omega^+})$, such that:

$$(i): \begin{cases} \nabla \times \mathbf{Q}_{L,r_0}^{tot}(\mathbf{r}) = \gamma_L \mathbf{Q}_{L,r_0}^{tot}(\mathbf{r}) \\ \nabla \times \mathbf{Q}_{R,r_0}^{tot}(\mathbf{r}) = -\gamma_R \mathbf{Q}_{R,r_0}^{tot}(\mathbf{r}) \end{cases} \quad \mathbf{r} \in \Omega^+$$

$$(ii): \hat{\mathbf{n}} \times \mathbf{Q}_{L,r_0}^{tot}(\mathbf{r}) = -\hat{\mathbf{n}} \times \mathbf{Q}_{R,r_0}^{tot}(\mathbf{r}) \quad \mathbf{r} \in S = \partial\Omega^- \quad (5)$$

$$(iii): \begin{cases} \hat{\mathbf{r}} \times \mathbf{Q}_{L,r_0}^{sc}(\mathbf{r}) + i\mathbf{Q}_{L,r_0}^{sc}(\mathbf{r}) = o(\frac{1}{r}) \\ \hat{\mathbf{r}} \times \mathbf{Q}_{R,r_0}^{sc}(\mathbf{r}) - i\mathbf{Q}_{R,r_0}^{sc}(\mathbf{r}) = o(\frac{1}{r}) \end{cases} \quad r \rightarrow \infty$$

The limits on radiation conditions (5(iii)), are taken uniformly in all directions $\hat{\mathbf{r}} \in S^2$, where S^2 is the unit sphere in \mathbb{R}^3 and $\hat{\mathbf{n}}$ is the outward normal unit vector perpendicular to the surface on the scatterer.

The incident electromagnetic wave ($\mathbf{E}_{r_0}^{inc}(\mathbf{r})$, $\mathbf{H}_{r_0}^{inc}(\mathbf{r})$) on the scatterer Ω^- generates the corresponding scattered field

($\mathbf{E}_{r_0}^{sc}(\mathbf{r})$, $\mathbf{H}_{r_0}^{sc}(\mathbf{r})$). The scattered electric field will be depended on the polarizations $\hat{\mathbf{p}}_L$, $\hat{\mathbf{p}}_R$, (see [4] (issue 2, p. 9, relation (6))) and will have the decomposition

$$\mathbf{E}_{r_0}^{sc}(\mathbf{r} | \hat{\mathbf{p}}_L, \hat{\mathbf{p}}_R) = \mathbf{Q}_{L,r_0}^{sc}(\mathbf{r} | \hat{\mathbf{p}}_L, \hat{\mathbf{p}}_R) + \mathbf{Q}_{R,r_0}^{sc}(\mathbf{r} | \hat{\mathbf{p}}_L, \hat{\mathbf{p}}_R) \quad (6)$$

where $\mathbf{Q}_{L,r_0}^{sc}(\mathbf{r} | \hat{\mathbf{p}}_L, \hat{\mathbf{p}}_R)$ and $\mathbf{Q}_{R,r_0}^{sc}(\mathbf{r} | \hat{\mathbf{p}}_L, \hat{\mathbf{p}}_R)$ are the corresponding scattered Beltrami fields which have the following behavior, when $r \rightarrow \infty$, [5], [7],

$$\mathbf{Q}_{A,r_0}^{sc}(\mathbf{r} | \hat{\mathbf{p}}_L, \hat{\mathbf{p}}_R) = h_0(\gamma_A r) \cdot \mathbf{g}_{A,r_0}(\hat{\mathbf{r}} | \hat{\mathbf{p}}_L, \hat{\mathbf{p}}_R) + o(\frac{1}{r^2}) \quad (7)$$

with $A = L, R$. The functions \mathbf{g}_{L,r_0} and \mathbf{g}_{R,r_0} are the LCP and RCP far-field patterns respectively, which are defined by the following relationship [7],

$$\mathbf{g}_{A,r_0}(\hat{\mathbf{r}} | \hat{\mathbf{p}}_L, \hat{\mathbf{p}}_R) = \int_S \hat{\mathbf{n}} \times [\gamma_A \nabla \times \mathbf{E}_{r_0}^{sc}(\mathbf{r}' | \hat{\mathbf{p}}_L, \hat{\mathbf{p}}_R) - \varpi_A \gamma^2 \mathbf{E}_{r_0}^{sc}(\mathbf{r}' | \hat{\mathbf{p}}_L, \hat{\mathbf{p}}_R) e^{-i\gamma_A r \cdot \mathbf{r}'}] ds(\mathbf{r}') \quad (8)$$

$$\text{With } \varpi_A = \begin{cases} -1, A = L \\ 1, A = R \end{cases}, \quad \gamma^2 = \gamma_L \gamma_R.$$

Near-field Inverse problem

Using the exact solution found in the paper [4] (issue 2, pp. 10-12) and considering appropriate asymptotic forms of the Bessel and Hankel functions in low frequencies, i.e. $|\gamma_A a| \ll 1$, calculate asymptotic expressions of the coefficients a_n^L , a_n^R , b_n^L and b_n^R . Specifically we have [3],

$$a_n^L \sim \frac{1 + \beta k}{2i\zeta_n^2(2n+1)} (\gamma_L a)^{2n+1} \quad \gamma_L a \rightarrow 0 \quad (9)$$

$$a_n^R \sim -\frac{i}{2n\zeta_n^2} \frac{(1 - \beta k)^{n+2}}{(1 + \beta k)^{n+1}} (\gamma_L a)^{2n+1}$$

$$\mathbf{E}_{r_0}^{sc}(\mathbf{r}_0 | \hat{\mathbf{p}}_L) = \sum_{n=1}^{\infty} \frac{n(n+1)}{2} B_n^L a_n^L \{ (h_n(\gamma_L r_0) \hat{\mathbf{x}} + \tilde{h}_n(\gamma_L r_0) \hat{\Psi}) + i(\tilde{h}_n(\gamma_L r_0) \hat{\mathbf{x}} - h_n(\gamma_L r_0) \hat{\Psi}) \} + \sum_{n=1}^{\infty} \frac{n(n+1)}{2} B_n^L a_n^R \{ (h_n(\gamma_R r_0) \hat{\mathbf{x}} - \tilde{h}_n(\gamma_R r_0) \hat{\Psi}) + i(-\tilde{h}_n(\gamma_R r_0) \hat{\mathbf{x}} - h_n(\gamma_R r_0) \hat{\Psi}) \} \quad (11)$$

Using the asymptotic relations:

$$\frac{h_n(\gamma_A r_0)}{h_0(\gamma_A r_0)} \sim \frac{\zeta_n}{(\gamma_A r_0)^n}$$

$$\frac{\tilde{h}_n(\gamma_A r_0)}{h_0(\gamma_A r_0)} \sim \frac{-n\zeta_n}{(\gamma_A r_0)^{n+1}} \quad (12)$$

$$\tilde{h}_n(\gamma_A a) \sim -\frac{n\zeta_n}{i(\gamma_A a)^{n+2}}$$

or

$$b_n^L \sim -\frac{i}{2n\zeta_n^2} \frac{(1 + \beta k)^{n+2}}{(1 - \beta k)^{n+1}} (\gamma_R a)^{2n+1} \quad \gamma_R a \rightarrow 0 \quad (10)$$

$$b_n^R \sim -\frac{i(1 - \beta k)}{2\zeta_n^2(2n+1)} (\gamma_R a)^{2n+1}$$

Where

$$\zeta_n = 1 \cdot 3 \cdot 5 \cdots (2n-1) = (2n)! / (2^n n!)$$

In the inverse problem we calculate the scattered near-field in the source $\mathbf{r} = \mathbf{r}_0$. By the relation (21), in work [4], with $\mathbf{r} = \mathbf{r}_0$ and for LCP incidence, we obtain [3],

with $\gamma_A r_0 \rightarrow 0$, $A = L, R$ and the series,

$$\begin{cases} \sum_{n=1}^{\infty} \tau^{2n+1} = \frac{\tau^3}{1 - \tau^2} \\ \sum_{n=1}^{\infty} n^2 \tau^{2n+1} = \frac{\tau^3(1 + \tau^2)}{(1 - \tau^2)^3} \end{cases} \quad (13)$$

$$\sum_{n=1}^{\infty} (2n+1) \tau^{2n+1} = \frac{\tau(3\tau^2 - \tau^4)}{(1 - \tau^2)^2} \quad (14)$$

$$\sum_{n=1}^{\infty} n(2n+1)\tau^{2n+1} = \frac{\tau(3\tau^2 + \tau^4)}{(1-\tau^2)^3} \quad (15)$$

$$\sum_{n=1}^{\infty} \frac{2n+1}{n} \tau^{2n+1} = \quad (16)$$

$$= \frac{\tau[\tau^2 \ln(1-\tau^2) + 2\tau^2 - \ln(1-\tau^2)]}{\tau^2 - 1}$$

and because of the relationships:

$$\frac{Y_R}{Y_L} = \frac{1-\beta k}{1+\beta k}, \quad 0 < \tau < 1,$$

where $\tau = a/r_0$, we obtain from (11) [3],

$$\begin{aligned} \mathbf{E}_{r_0}^{sc}(\mathbf{r}_0 | \hat{\mathbf{p}}_L) &\sim \\ &\sim \frac{(1+\beta k)}{2(Y_L a)^2} \frac{\tau^5}{(1-\tau^2)^3} \cdot \hat{\mathbf{p}}_L \end{aligned} \quad (17)$$

Therefore the measure of the scattered field $\mathbf{E}_{r_0}^{sc}(\mathbf{r}_0 | \hat{\mathbf{p}}_L)$ is

$$|\mathbf{E}_{r_0}^{sc}(\mathbf{r}_0 | \hat{\mathbf{p}}_L)| \sim \frac{(1+\beta k)}{2(Y_L a)^2} \frac{\tau^5}{(1-\tau^2)^3} \quad (18)$$

$$Y_L a \rightarrow 0$$

Similarly for the RCP incidence, we have that

$$|\mathbf{E}_{r_0}^{sc}(\mathbf{r}_0 | \hat{\mathbf{p}}_R)| \sim \frac{(1-\beta k)}{2(Y_R a)^2} \frac{\tau^5}{(1-\tau^2)^3} \quad (19)$$

$$Y_R a \rightarrow 0$$

Finally, based on the relationships (18) and (19), we conclude that

$$\begin{aligned} |\mathbf{E}_{A,r_0}^{sc}(\mathbf{r}_0 | \hat{\mathbf{p}}_A)| &\sim \\ &\sim \frac{(1-\varpi_A \beta k)}{2(Y_A a)^2} \frac{\tau^5}{(1-\tau^2)^3} \end{aligned} \quad (20)$$

$$Y_A a \rightarrow 0, \quad A = L, R$$

Choose a Cartesian coordinate system $Ox\psi z$, and five point-source locations, namely $O(0, 0, 0)$, $A_1(l, 0, 0)$, $A_2(0, l, 0)$, and $A_4(0, 0, 2l)$, which are at (unknown) distances r_0, r_1, r_2, r_3 and r_4 , respectively from the sphere's center K . The parameter l is a chosen fixed length. The sizes of the resulting five measurements $|\mathbf{E}_{A,r_j}^{sc}(\mathbf{r}_j | \hat{\mathbf{p}}_A)|$ are

$$M_j = \frac{2(Y_L Y_R)l}{(1-\varpi_A \beta k)} |\mathbf{E}_{A,r_j}^{sc}(\mathbf{r}_j | \hat{\mathbf{p}}_A)| \quad (21)$$

and

$$\rho_j = \frac{r_j}{l}, \quad b = \sqrt{\frac{a}{l}} \quad (22)$$

where $j = 0, 1, 2, 3, 4$. Therefore we have the following five measurements

$$M_j = \frac{b^5 \rho_j}{(\rho_j^2 - b^4)^3} \quad (23)$$

with $\rho_j > b^2 > 0$. Applying the law of cosines in triangle KOA_4 and using that

$$r_j = \rho_j l \quad (24)$$

we obtain

$$\rho_4 = 2 + 2\rho_3 - \rho_0 \quad (25)$$

Because of (24), we take

$$\begin{aligned} \rho_j^6 - 3\rho_j^4 b^4 + 3\rho_j^2 b^8 - \\ - b^{12} - b^5 \frac{\rho_j}{M_j} = 0 \end{aligned} \quad (26)$$

Thus in equation (26) identified the ρ , with $j = 0, 1, 2, 3, 4$. If the radius a of the sphere is known, solve the system of six algebraic equations (25) and (26). Also if you consider that the radius

a is too small so that $a \ll l$, then the relationship (23) shows [3],

$$M_j = \frac{b^5}{\rho_j^5} \quad (27)$$

so we have the following system of equations

$$\begin{cases} \rho_4 = 2 + 2\rho_3 - \rho_0 \\ \rho_j^5 M_j - b^5 = 0 \end{cases} \quad (28)$$

where $j = 0, 1, 2, 3, 4$.

References

- [1] Athanasiadis C., Martin P.A., Stratis I.G., "On spherical-wave scattering by a spherical scatterer and related near-field inverse problems", *IMA Journal of Applied Mathematics*, Vol. 66, 2001, pp. 539-549
- [2] Athanasiadis C., Martin P.A., Stratis I.G., "On the Scattering of Point-generated Electromagnetic Waves by a perfectly Conducting Sphere, and Related Near-field Inverse Problems", *Zeitschrift für Angewandte Mathematik und Mechanik*, Vol. 83, Issue 2, 2003, pp. 129-136
- [3] Berketis M. Nikolaos, "Scattering spherical Electromagnetic waves in chiral media", PhD thesis, University of Athens - Department of Mathematics, December 2007
- [4] Berketis N.M., "Direct and related far-field inverse scattering problems for spherical electromagnetic waves in chiral media", *FunkTechnikPlus # Journal*, Issue 2, November 2013, pp. 7-18
"www.otoiser.org/index.php/ftpj/article/view/26"
- [5] Lakhtakia A., "Beltrami Fields in Chiral Media", *World Scientific*, Singapore, 1994, §2-1.3 (pp. 42-44), §2-2.3 (pp. 49-52), §4-1 (p. 130 Chapter 4), §5-1 (p. 164 Chapter 5), §6-1.1 (pp. 214-397), §8-2.1 (pp. 391-397), §9-2.3 (pp. 468- 473)

[This Page Intentionally Left Blank]

- [6] Lakhtakia A, Varadan V.K., Varadan V.V., "Time-Harmonic Electromagnetic Fields in Chiral Media", Lecture Notes in Physics, Vol. 335, Springer, Berlin, 1989, §3-§4-§7-§11-§12-§13
- [7] Athanasiadis C., "On the far field patterns for electromagnetic scattering by a chiral obstacle in a chiral environment", Journal of Mathematical Analysis and Applications, Vol. 309, 2005, pp. 517-533
- [8] Morse P.M, Feshbach H., "Methods of Theoretical Physics, Part II", Mc Graw-Hill, 1953, pp. 1864-1866, 1870, 1871, 1887

Previous Publication in FUNKTECHNIKPLUS # JOURNAL

"Direct and Related Far-Field Inverse Scattering Problems for Spherical Electromagnetic Waves in Chiral Media",
Issue 2, pp. 7-18

Preprint Versions

"Direct and inverse scattering problems for spherical
Electromagnetic waves in chiral media",
Christodoulos Athanasiadis and Nikolaos Berketis,
"http://arxiv.org/abs/0812.2169"

*** About the Author**

Nikolaos Berketis, Issue 2, p. 18

[This Page Intentionally Left Blank]

In case of any doubt,
download the genuine papers from
genuine.ftpj.otoiser.org

FRONT COVER VIGNETTE

A faded synthesis of an anthemion rooted in a meandros

The thirteen-leaf is a symbol for a life tree leaf.
"Herakles and Kerberos", ca. 530–500 BC,
by Paseas, the Kerberos Painter,
Museum of Fine Arts, Boston.

www.mfa.org/collections/object/plate-153852

The simple meandros is a symbol for eternal immortality.
"Warrior with a phiale", ca. 480–460 BC,
by Berliner Maler,
Museo Archeologico Regionale "Antonio Salinas" di Palermo.

commons.wikimedia.org/wiki/File:Warrior_MAR_Palermo_NI2134.jpg